

UNCLASSIFIED

AD 401 416

*Reproduced
by the*

DEFENSE DOCUMENTATION CENTER

FOR

SCIENTIFIC AND TECHNICAL INFORMATION

CAMERON STATION, ALEXANDRIA, VIRGINIA



UNCLASSIFIED

NOTICE: When government or other drawings, specifications or other data are used for any purpose other than in connection with a definitely related government procurement operation, the U. S. Government thereby incurs no responsibility, nor any obligation whatsoever; and the fact that the Government may have formulated, furnished, or in any way supplied the said drawings, specifications, or other data is not to be regarded by implication or otherwise as in any manner licensing the holder or any other person or corporation, or conveying any rights or permission to manufacture, use or sell any patented invention that may in any way be related thereto.

10

6332

NOLC REPORT 580

1 APRIL 1963

ASTIA
CATALOGED BY
AS AD NO. 401 416

N-LOOP VLF SUPERDIRECTIVE ARRAYS

E. W. SEELEY

RESEARCH DEPARTMENT

401 416

ASTIA
RECEIVED
APR 29 1963
TISIA A



NAVAL ORDNANCE LABORATORY CORONA

CORONA, CALIFORNIA

NAVAL ORDNANCE LABORATORY CORONA

W. R. KURTZ, CAPT., USN
Commanding Officer

F. S. ATCHISON, Ph.D.
Technical Director

FOREWORD

The work described in this report was conducted in the Electronics Division as a part of the NOLC very-low-frequency research program, which is jointly sponsored by this Laboratory's Foundational Research program, WepTask R360-FR-104/211-1/R011-01-001, and the Office of Naval Research, Code 418, under P. O. 3-0012.

C. J. HUMPHREYS
Head, Research Department

ABSTRACT

Superdirectivity may be achieved with short VLF loop arrays because the beam width depends only upon the number of loops and not upon the length of the array. In addition, the usual factors limiting superdirectivity are not as prevalent in these arrays because of the decoupling between VLF loops.

Expressions are derived for the beam width, effective height, reception pattern, amplitude and position of the back lobes, and the effects of voltage phase and amplitude differences between loops. These equations describe short arrays of any number of loops. The most serious limitation concerning the directivity of superdirective loop arrays is caused by the voltage phase and amplitude differences between loops. These differences between adjacent loops combine to obscure the nulls and deteriorate the reception pattern.

CONTENTS

	<u>Page</u>
Introduction	1
Radiation Pattern Characteristics	1
Effective Height	6
The Effect of Phase and Amplitude Errors	6
Summary and Conclusions	7
References	8

INTRODUCTION

The superdirective antenna of infinitesimally small size, with its possibility of infinite gain, has been discussed by several authors (Ref. 1-6). These authors have pointed out that such arrays are impractical because of basic limitations such as narrow bandwidth, high losses, and critical tolerances in individual loop voltages. Nevertheless, moderate superdirectivity has been achieved (Ref. 7, 8) with practical arrays. It has been shown (Ref. 8) that superdirectivity can be obtained from radiators that are decoupled from one another. The elements of receiving arrays at VLF can very easily be decoupled since they are so small compared with the wavelength.

At very low frequencies, it is very difficult to obtain highly directive antenna patterns. Large tracts of land are needed because of the long wavelengths involved. However, it appears that arrays can be greatly reduced in size by using the principle of superdirectivity. Considerable directivity can be achieved with a superdirective loop array that is only a small fraction of a wavelength in size. These superdirective receiving antennas are possible at VLF because the decoupling between loops (Ref. 9) makes the usual limiting factors, such as narrow bandwidth and high losses, extremely small. The critical tolerance in individual loop voltages is the factor that limits the number of loops (n) that can be used, which limits the directivity.

The characteristics and performance of short two- and three-loop arrays have been discussed previously (Ref. 9 and 10). This report will expand the subject to include the radiation pattern characteristics, the effective height, and the effect of phase and amplitude errors on the short n -loop superdirective array.

RADIATION PATTERN CHARACTERISTICS

In this section, the important characteristics of the n -loop array pattern are deduced from corresponding equations of the two- and three-loop arrays. Equations for the positions of the side lobes and side nulls, the beam width, and the ratios of side lobe and back lobe to front lobe are presented.

The horizontal pattern of the horizontal array with the planes of the loops oriented in a vertical plane (Ref. 9) is shown in Figure 1. This pattern is described by equations (1), (2), and (3). For the two-loop array

$$|E_{\varphi}| = \cos \varphi \left[\frac{2\pi D}{\lambda} (\cos \varphi - \cos \varphi_0) \right] \quad (1)$$

and for the three-loop array

$$|E_{\varphi}| = \cos \varphi \left[\frac{2\pi D}{\lambda} (\cos \varphi - \cos \varphi_0) \right]^2 \quad (2)$$

where

E_{φ} = relative voltage received from direction φ compared with the voltage from one loop

φ = angle of received signal in the horizontal plane measured from the plane of loops

D = distance between loops

λ = free-space wavelength

In these equations, $D \ll \lambda$, and there is a phase difference of $\delta - \pi$ between identical adjacent loops, where δ is the delay between adjacent loops. By mathematical induction, the pattern for the n -loop array is described as

$$|E_{\varphi}| = \cos \varphi \left[\frac{2\pi D}{\lambda} (\cos \varphi - \cos \varphi_0) \right]^{n-1} \quad (3)$$

Equation (3) is expressed in terms of (a) distance between loops in wavelengths, D/λ , and (b) the null position, φ_0 , that is located between the back lobe and the side lobes (see Figure 1). For the n -loop array, the null position depends upon the delay between adjacent loops and the free-space propagation time between loops, as expressed by

$$\varphi_0 = \arccos \frac{\delta}{D/v_0} \quad (4)$$

where v_0 is the velocity of light. The null position may be moved about the back half of the pattern to reject unwanted signals by varying the delay, δ , between adjacent loops.





FIGURE 1. Superdirective Array

The beam width is a measure of the directivity of an antenna. The half-power beam width, $2\varphi_A$, of the n -loop array in terms of the null position is

$$\cos \varphi_A = 0.707 \left(\frac{1 - \cos \varphi_0}{\cos \varphi_A - \cos \varphi_0} \right)^{n-1} \quad (5)$$

when $D \ll \lambda$. The narrowest beam width occurs when the null position approaches 90 deg. Then

$$2\varphi_A = 2 \arccos \sqrt[n]{0.707} \quad (6)$$

When the null position is at 180 deg, the beam width is greatest. The beam widths at these two extremes are plotted in Figure 2 as a function of the number of loops in the array. There is a spread of only about 10 deg between the extremes where the numbers of loops are greater. The beam width is not a function of the distance between loops, and herein lies the possibility of obtaining superdirectivity.

The amplitudes of the back lobes are an indication of the unidirectional properties of the array pattern. Although there are three back lobes, one at $\varphi = 180$ deg and two symmetrically located about this one (see Figure 1), only the lobe at $\varphi = 180$ deg is called the back lobe; the two lobes on either side of the back lobe are called side lobes. The ratio of the front lobe to the back lobe as derived from equation (3) is

$$R_0 = \left(\frac{1 - \cos \varphi_0}{1 + \cos \varphi_0} \right)^{n-1} \quad (7)$$

It is obvious from equation (7) that a large number of loops in the array would cause the back lobe to be much smaller than the front lobe. The front-lobe-to-side-lobe ratio can also be derived from equation (3). To do this, the position of the side lobe maximum must first be determined by differentiating equation (3) and equating the results to zero. Then the position of the side lobe is

$$\varphi_1 = \arccos \left(\frac{1}{n} \cos \varphi_0 \right) \quad (8)$$

Equation (8) can now be used in conjunction with (3) to derive the front-lobe-to-side-lobe ratio, which is

$$R_1 = \left(\frac{n}{\cos \varphi_0} \right)^n \left(\frac{1 - \cos \varphi_0}{1 - n} \right)^{n-1} \quad (9)$$




FIGURE 2. Beam Widths and Effective Heights for Superdirective Arrays

From equations (7) and (9), it is obvious that the loop array patterns become very unidirectional as the number of loops is increased. This is important in applications where the loop array is in a field of multiple sources, such as sferics at VLF.

EFFECTIVE HEIGHT

Moderately narrow beams can be achieved with a few loops, but in return, the effective height is reduced; this is shown in Figure 2. The effective height of an n-loop array as derived from equation (3) is

$$h_e = 20(n - 1) \log_{10} \left[\frac{2\pi D}{\lambda} (1 - \cos \varphi_0) \right] \quad (10)$$

This is the effective height in db for an n-loop array compared with that for a one-loop array. In Figure 2, the effective height is plotted versus the number of loops for three different array lengths. The vertical distance between equal-array-length curves indicates the range of effective heights for null positions from 90 deg to 180 deg. The very small effective heights of the shorter arrays could make them impractical unless loops with very large effective heights are used to make up the array. Large ground-return inverted loops or perhaps short Beverage antennas would be a practical element to use because of their large effective heights.

THE EFFECT OF PHASE AND AMPLITUDE ERRORS

The foregoing analysis has assumed that the received signals have been of equal amplitude and that each loop voltage has had the proper phase to cancel at the null angles. As the number of loops is increased, any departure from this assumption will reduce the null depths. An analysis of the null voltage where there are small inequalities in loop-voltage phase and amplitude has been made (Ref. 9). The resultant null voltage was found to be the sum of the voltage amplitude differences between adjacent loops, $\Delta e_{n-1, n}$, in quadrature with the sum of the phase differences in radians between adjacent loops, $\Delta \theta_{n-1, n}$, which is expressed as

$$E_r = \left| \sum_2^n \Delta e_{n-1, n} - jE_L \sum_2^n \Delta \theta_{n-1, n} \right| \quad (11)$$

where E_L is the amplitude of the voltage from one loop. The voltage differences between adjacent loops will tend to deteriorate the reception pattern as the number of loops is increased. Because highly directive loop arrays require accurate matching of individual loops and delay lines, the feasibility of a practical array will depend upon the degree of accuracy attainable, and this can only be determined by experiment.

SUMMARY AND CONCLUSIONS

Superdirectivity may be achieved with short VLF loop arrays because the beam width is not a function of the length of the array but of the number of loops in the array. Also, the usual limiting factors in superdirective arrays, such as narrow bandwidth and high losses, are extremely small because of the decoupling between loops at long wavelengths. The directivity is limited, however, by the critical tolerance in adjacent loop voltages.

The effective height and all of the pattern characteristics of the short array, such as beam width and back-lobe amplitude and position, can be expressed in terms of the selected null position and the distance between loops for a given number of loops. The assumption is made that the distance between loops is much smaller than a wavelength, which is valid at VLF. The directivity is increased by the number of loops used in the array. Equations (6), (7), and (9) bear this out in that the beam width and back lobes become smaller as the number of loops increases.

The two limiting factors that affect the directivity are effective height and unequal voltages between loops. The very small effective heights of the shorter arrays could make them impractical unless very large loops are used. The most serious limitation on the directivity of an array with a large number of loops is caused by the voltage-amplitude and phase differences between loops. These differences between adjacent loops will obscure the nulls and deteriorate the reception pattern. Equation (11) shows that the differences add together as the number of loops is increased. The feasibility of designing highly directive loop arrays will depend on the accuracy with which the individual loops and delay lines can be matched; this must be experimentally determined.

REFERENCES

1. Schelkunoff, S. A. "A Mathematical Theory of Linear Arrays," Bell System Tech. J., Vol. 22 (January 1943), pp. 80-107.
2. Schelkunoff, S. A., and H. T. Friis. Antenna Theory and Practice. John Wiley & Sons, Inc., New York, 1952. P. 195.
3. Riblet, H. J. "Note on the Maximum Directivity of an Antenna," Proc. Inst. Radio Engrs., Vol. 36 (May 1948), pp. 620-24.
4. Taylor, T. T. "A Discussion of the Maximum Directivity of an Antenna," Proc. Inst. Radio Engrs., Vol. 36 (September 1948), p. 1135.
5. Yaru, N. "A Note on Super-Gain Antenna Arrays," Proc. Inst. Radio Engrs., Vol. 39 (September 1951), pp. 1081-85.
6. Stearns, C. O. Computed Performance of Moderate Size Super-gain Antennas. NBS Report 6797, 5 September 1961.
7. Elliott, R. S. A Five-Element Supergain Dipole Array. Hughes Aircraft Co. Tech. Memo 380, October 1954.
8. Spitz, E. Supergain and Volumetric Antennas. Compagnie Général de Télégraphie Sans Fil, 15 June 1959. (Technical final report, Contract No. AF61(052)-102; U. S. Air Force Cambridge Research Center Tech. Report 59-194)
9. Seeley, E. W. "Two- and Three-Loop Superdirective Receiving Antennas," J. Research Natl. Bur. Standards - Section D Radio Propagation, Vol. 67D, No. 2 (March-April 1963).
10. Friis, H. T. "A New Directional Receiving System," Proc. Inst. Radio Engrs., Vol. 13 (December 1925), pp. 685-707.

INITIAL DISTRIBUTION

	<u>Copies</u>		<u>Copies</u>
Chief of Naval Research		Commanding Officer & Director	
Navy Department		Navy Electronics Laboratory	
Washington 25, D. C.		San Diego 52, Calif.	
Attn: Code 418	5	Attn: Library	1
420C	1		
427	1	Director, Special Projects	
463	1	Navy Department	
		Washington 25, D. C.	
Chief, Bureau of Naval Weapons		Attn: SP-2041	1
Navy Department		CDR T. Christman, SP 270	1
Washington 25, D. C.			
Attn: R-12, Dr. E. S. Lamar	1	Commanding Officer	
Chief, BuWeps	1	Naval Ordnance Laboratory	
Code DLI-31	4	White Oak	
		Silver Spring, Md.	
Chief of Naval Operations		Attn: R. J. Miller, DRP	1
Navy Department			
Washington 25, D. C.		Commanding Officer	
Attn: Code Op-07TE	1	Naval Ordnance Test Unit	
Op-70	1	Patrick Air Force Base, Fla.	
Op-733	1	Attn: N3	1
Op-92	1		
Op-92B3	1	Commander	
		Naval Air Test Center	
Director		Patuxent River, Md.	
Naval Research Laboratory		Attn: Weapons Systems Test	
Washington 25, D. C.		Division (Code 424)	1
Attn: Code 2027	1		
5320	1	Headquarters	1
		U. S. Air Force	
Commander		(AFTAC/TD-5)	
Naval Missile Center		Washington 25, D. C.	
Point Mugu, Calif.			
Attn: Tech Library,		Headquarters, U. S. Air Force	1
Code N03022	1	Office of Assistant Chief of	
		Staff, Intelligence	
Chief, Bureau of Ships		Intelligence Systems Branch (AFCIN-P2)	
Navy Department		Washington 25, D. C.	
Washington 25, D. C.			
Attn: Code 362A	1		

	<u>Copies</u>		<u>Copies</u>
Headquarters		Commanding General	
Space Systems Division		U. S. Army Materiel Command	
Air Force Systems Command		Building T-7	
U. S. Air Force		Washington 25, D. C.	
Air Force Unit Post Office		Attn: AMCRD-DE	1
Los Angeles 45, Calif.			
Attn: SSZC	1	Chief, U. S. Army Security Agency	
		Arlington Hall Station	
Headquarters		Arlington 12, Va.	
North American Air Defense		Attn: LADEV-S	1
Command			
Ent Air Force Base		Commander	
Colorado Springs, Colo.		Redstone Scientific Information Center	
Attn: NELC (Advanced Projects		U. S. Army Missile Command	
Group)	1	Redstone Arsenal, Ala.	
		Attn: J. E. Norman	1
Headquarters			
Rome Air Development Center		Commanding Officer	1
Air Force Systems Command		U. S. Army Signal Electronic	
U. S. Air Force		Research Unit	
Griffiss Air Force Base, N. Y.		P. O. Box 205	
Attn: RALTT, F. C. Bradley	1	Mountain View, Calif.	
RAUEL-3, B. Cooper	1		
Headquarters	1	Commanding Officer	
Strategic Air Command		U. S. Army Signal Radio Propagation	
Offutt Air Force Base, Nebr.		Agency	
		Ft. Monmouth, N. J.	
		Attn: SIGRP-A	1
Headquarters			
Air Force Cambridge Research Lab.		Commanding Officer	
Laurence G. Hanscom Field		U. S. Army Signal Missile	
Bedford, Mass.		Support Agency	
Attn: CRRK, Dr. P. Newman	1	White Sands Missile Range, N. Mex.	
CRRI, W. F. Ring	1	Attn: SIGWS-PO	1
Headquarters			
Foreign Technology Division		Systems Branch	
Wright-Patterson Air Force Base		U. S. Army Scientific Liaison &	
Ohio		Advisory Group	
Attn: ID-A3a	1	P. O. Box 7157	
ID-E1B	1	Apex Station	
TD-XA	1	Washington 4, D. C.	
		Attn: N. Garofalo	1

	<u>Copies</u>		<u>Copies</u>
Institute for Defense Analyses		Director	1
1825 Connecticut Ave., N. W.		Defense Atomic Support Agency	
Washington 6, D. C.		Data Center	
Attn: RESD, Dr. P. Van Handel	1	P. O. Drawer QQ	
RESD, Dr. C. Angulo	1	Santa Barbara, Calif.	
Dr. N. L. Muench	1		
Commanding Officer		Director	
Picatinny Arsenal		National Security Agency	
Dover, N. J.		Fort George G. Meade, Md.	
Attn: Tech. Info. Library	1	Attn: C3/TDL	1
Director		ACF Electronics Division	
Advanced Research Projects Agency		ACF Industries, Inc.	
Washington 25, D. C.		3355 - 52nd Avenue	
Attn: LCDR D. Chandler	1	Hyattsville, Md.	
J. Ruina	1	Attn: W. T. Whelan (R&D)	1
Dr. C. A. Pearse	1	Aero-Geo Astro Corporation	1
A. Van Every	1	Box 1082	
Director	1	Edsall & Lincoln Rd.	
Weapons Systems Evaluation Group		Alexandria, Va.	
Room 1E875, The Pentagon		Aero-Geo Astro Corporation	
Washington 25, D. C.		13624 Magnolia Avenue	
Armed Services Technical	10	Corona, Calif.	
Information Agency		Attn: A. Walters	1
Arlington Hall Station		Applied Physics Laboratory	
Arlington 12, Va.		8621 Georgia Avenue	
Director		Silver Spring, Md.	
National Bureau of Standards		Attn: Dr. W. H. Avery	1
Boulder, Colo.		Magnavox Research Laboratories	
Attn: R. C. Kirby (Chief, Radio		2829 Maricopa Street	
Systems Div.)	1	Torrance, Calif.	
L. H. Tveten (HF/VHF		Attn: N. F. Loretz, Head, Advanced	
Research Section)	1	Development Department	1

	<u>Copies</u>		<u>Copies</u>
Massachusetts Institute of Technology		Stanford Research Institute	
Radio Physics Division		Communication & Propagation Lab.	
Lincoln Laboratory		Menlo Park, Calif.	
P. O. Box 73		Attn: R. L. Leadabrand	1
Lexington 73, Mass.		L. T. Dolphin, Jr.	1
Attn: Dr. J. V. Harrington	1		
Dr. J. H. Chisholm (Radio		University of California	
Propagation Group)	1	Berkeley 4, Calif.	
M. L. Stone (Radio		Attn: Dr. E. Pinney	1
Propagation Group)	1		
Pickard and Burns, Inc.		Institute of Science & Technology	
103 4th Avenue		The University of Michigan	
Waltham 54, Mass.		P. O. Box 618	
Attn: Dr. J. Williams	1	Ann Arbor, Mich.	
		Attn: BAMIRAC-ad	1
Radio Corporation of America		The University of Michigan	
Aerospace Communications &		Radiation Laboratory	
Controls Division		201 Catherine Street	
Burlington, Mass.		Ann Arbor, Mich.	
Attn: J. Rubinovitz	1	Attn: Dr. R. J. Leite	1
The Rand Corporation		Westinghouse Electric Corporation	1
1700 Main Street		Defense Center-Baltimore	
Santa Monica, Calif.		Technical Information Center	
Attn: Dr. C. M. Crain	1	P. O. Box 1693	
		Baltimore 3, Md.	
Raytheon Company		NOLC:	
Communications & Data Processing		C. J. Humphreys, Code 40	1
Operations		F. C. Essig, Code 45	1
1415 Boston-Providence Turnpike		E. W. Seeley, Code 452	5
Norwood, Mass.		V. E. Hildebrand, Code 453	1
Attn: L. C. Edwards	1	Technical Library, Code 234	2
Stanford Electronics Laboratories			
Stanford University			
Stanford, Calif.			
Attn: Dr. O. G. Villard	1		
University of New Mexico			
Albuquerque, N. Mex.			
Attn: R. K. Moore	1		

<p>Naval Ordnance Laboratory Corona. (NOLC Report 580)</p> <p>N-LOOP VLF SUPERDIRECTIONAL ARRAYS, by E. W. Seeley, Research Department. 1 April 1963. 12 pp. UNCLASSIFIED</p> <p>Superdirectivity may be achieved with short VLF loop arrays because the beam width depends only upon the number of loops and not upon the length of the array. In addition, the usual factors limiting superdirectivity are not as prevalent in these arrays because of the decoupling between VLF loops.</p> <p>Expressions are derived for the beam width, effective height, reception pattern, amplitude and position of the back lobes, and the effects of voltage phase and amplitude differences between loops. These equations describe short arrays of any number of loops. The most serious limitation concerning the directivity of superdirective loop arrays is caused by the voltage phase and amplitude differences between loops. These differences between adjacent loops combine to obscure the nulls and deteriorate the reception pattern.</p>	<p>I. Very low frequency antennas - Performance</p> <p>I. Very Low Frequency Research Program</p> <p>II. Title</p> <p>III. Seeley, E. W.</p> <p>WepTask: R360-FR-104/211-1/R011-01-001</p> <p>ONR: P. O. 3-0012</p> <p>This card is UNCLASSIFIED</p>	<p>Naval Ordnance Laboratory Corona. (NOLC Report 580)</p> <p>N-LOOP VLF SUPERDIRECTIONAL ARRAYS, by E. W. Seeley, Research Department. 1 April 1963. 12 pp. UNCLASSIFIED</p> <p>Superdirectivity may be achieved with short VLF loop arrays because the beam width depends only upon the number of loops and not upon the length of the array. In addition, the usual factors limiting superdirectivity are not as prevalent in these arrays because of the decoupling between VLF loops.</p> <p>Expressions are derived for the beam width, effective height, reception pattern, amplitude and position of the back lobes, and the effects of voltage phase and amplitude differences between loops. These equations describe short arrays of any number of loops. The most serious limitation concerning the directivity of superdirective loop arrays is caused by the voltage phase and amplitude differences between loops. These differences between adjacent loops combine to obscure the nulls and deteriorate the reception pattern.</p>	<p>I. Very low frequency antennas - Performance</p> <p>I. Very Low Frequency Research Program</p> <p>II. Title</p> <p>III. Seeley, E. W.</p> <p>WepTask: R360-FR-104/211-1/R011-01-001</p> <p>ONR: P. O. 3-0012</p> <p>This card is UNCLASSIFIED</p>	<p>I. Very low frequency antennas - Performance</p> <p>I. Very Low Frequency Research Program</p> <p>II. Title</p> <p>III. Seeley, E. W.</p> <p>WepTask: R360-FR-104/211-1/R011-01-001</p> <p>ONR: P. O. 3-0012</p> <p>This card is UNCLASSIFIED</p>	<p>I. Very low frequency antennas - Performance</p> <p>I. Very Low Frequency Research Program</p> <p>II. Title</p> <p>III. Seeley, E. W.</p> <p>WepTask: R360-FR-104/211-1/R011-01-001</p> <p>ONR: P. O. 3-0012</p> <p>This card is UNCLASSIFIED</p>
--	--	--	--	--	--